

Chateau 5G



Modem	RM500Q-GL	Frequency bands	5G	LTE CAT	CAT16	Antenna count	4
5G NR NSA						38	41 77 78 79
5G NR SA	1 2 3	5 7 8 12		20 25	28	38	40 41 48 66 71 77 78 79
LTE-FDD	1 2 3 4	5 7 8 12	13 14 17 18 19	20 25 26 28 29 30 32			66 71
LTE-TDD						34 38	40 41 42 43 46 48

Modem	RM502Q-GL	Frequency bands	5G	LTE CAT	CAT20	Antenna count	4
5G NR NSA						38	41 77 78
5G NR SA	1 2 3	5 7 8 12		20 25	28	38	40 41 48 66 71 77 78 79
LTE-FDD	1 2 3 4	5 7 8 12	13 14 17 18 19	20 25 26 28 29 30 32			66 71
LTE-TDD						34 38	40 41 42 43 46 48

Modem	RM500Q-AE	Frequency bands	5G	LTE CAT	CAT16	Antenna count	4
5G NR NSA	1 2 3	5 7 8 12		20 25	28	38	40 41 48 66 71 77 78 79
5G NR SA	1 2 3	5 7 8 12		20 25	28	38	40 41 48 66 71 77 78 79
LTE-FDD	1 2 3 4	5 7 8 12	13 14 17 18 19	20 25 26 28 29 30 32			66 71
LTE-TDD						34 38	40 41 42 43 46 48

Modem	RM502Q-AE	Frequency bands	5G	LTE CAT	CAT20	Antenna count	4
5G NR NSA	1 2 3	5 7 8 12		20 25	28	38	40 41 48 66 71 77 78 79
5G NR SA	1 2 3	5 7 8 12		20 25	28	38	40 41 48 66 71 77 78 79
LTE-FDD	1 2 3 4	5 7 8 12	13 14 17 18 19	20 25 26 28 29 30 32			66 71
LTE-TDD						34 38	40 41 42 43 46 48

Modem	RG500Q-EA	Frequency bands	5G	LTE CAT	CAT16	Antenna count	8
5G NR NSA	1 3	5 7 8		20	28	38	40 41 77 78 79
5G NR SA	1 3	5 7 8		20	28	38	40 41 77 78 79
LTE-FDD	1 3	5 7 8	18 19 20	26 28	32		
LTE-TDD						34 38 39	40 41 42 43

Modem	RG502Q-EA	Frequency bands	5G	LTE CAT	CAT20	Antenna count	8
5G NR NSA	1 3	5 7 8		20	28	38	40 41 77 78 79
5G NR SA	1 3	5 7 8		20	28	38	40 41 77 78 79
LTE-FDD	1 3	5 7 8	18 19 20	26 28	32		
LTE-TDD						34 38 39	40 41 42 43